

Suppliers' Information Note

For The Openreach Network

Protocol Implementation Conformance Statements (PICS) for ISDN 30e: Primary Rate Access - Layer 2 TECHNICAL INFORMATION FOR SUPPLIERS

Each SIN is the copyright of British Telecommunications plc. Reproduction of the SIN is permitted only in its entirety, to disseminate information on the Openreach Network within your organisation. You must not edit or amend any SIN or reproduce extracts. You must not remove Openreach trademarks, notices, headings or copyright markings.

This document does not form a part of any contract with Openreach customers or suppliers.

Users of this document should not rely solely on the information in this document, but should carry out their own tests to satisfy themselves that terminal equipment will work with the Openreach network.

Openreach reserves the right to amend or replace any or all of the information in this document.

Openreach shall have no liability in contract, tort or otherwise for any loss or damage, howsoever arising from use of, or reliance upon, the information in this document by any person.

Due to technological limitations a very small percentage of customer interfaces may not comply with some of the individual characteristics which may be defined in this document.

Publication of this Suppliers' Information Note does not give or imply any licence to any intellectual property rights belonging to British Telecommunications plc or others. It is your sole responsibility to obtain any licences, permissions or consents which may be necessary if you choose to act on the information supplied in the SIN.

Those BT services marked ® indicates it is a registered trade mark of British Telecommunications plc.

Those BT services marked ™ indicates it is a trade mark of British Telecommunications plc.

This SIN is available in Portable Document Format (pdf) from:
<https://www.openreach.co.uk/orpg/home/helpandsupport/sins/sins.do>

Enquiries relating to this document should be directed to: orsinsfa@openreach.co.uk

1. Introduction

This document states the capabilities and options of the DSS1 Layer 2 protocol for basic call control on the primary rate access interface which has been implemented in the ISDN 30e network.

The ETSI protocol specification used as a basis for this PICS proforma is ETS 300 402-2, edition November 1995.

The ETSI PICS proforma used as a basis for this PICS is ETS 300 402-4, edition November 1996.

2. References

- 1 ETS 300 402-2 (1995) Integrated Services Digital Network (ISDN); Digital Subscriber Signalling System No. one (DSS1) protocol; Data link layer; Part 2: General protocol specification; [Application of ITU-T Recommendation Q.921 (1993), modified]
- 2 ETS 300 403-4 (1996) Integrated Services Digital Network (ISDN); Digital Subscriber Signalling System No. one (DSS1) protocol; Data link layer; Part 4: Protocol Implementation Conformance Statement (PICS) proforma specification

For further information or copies of referenced sources, please see document sources at <https://www.openreach.co.uk/orpg/home/helpandsupport/sins/sins.do>

3. Protocol Implementation Conformance Statement (PICS)

Using the relevant standard (see ref. 2), the PICS is given below. The section and table numbering as used in the ETSI standard has been maintained. Only those parts of the standard relevant to the network implementation are given. For guidance on the abbreviations and meaning of the completed PICS tables, see SIN 369, Part A.

Unless stated otherwise, the standard referred to in the **reference** column is the ETS given in reference 1. For glossary of terms used, see the referenced standards [1, 2].

A.6 Roles

Table A.1: Roles

Item	Role	Conditions for status	Status	Reference	Support
R 1	not used				
R 2.1	the user role		O.1		[]Yes [√]No
R 2.2	the network role		O.1		[√]Yes []No
	Type of implementation				
R 3	not used				
R 4	not used				
R 5	not used				
R 6.1	basic access		O.2		[]Yes [√]No
R 6.2	primary rate access		O.2		[√]Yes []No
O.1	Support of one and only one of these options is required.				
O.2	Support of one and only one of these options is required.				
Comments:					

A.8 Network

The tables provided in this subclause need only to be completed for network implementations.

Prerequisite: R 2.2

A.8.1 Major capabilities

Each question in table A.12 refers to a major function of the protocol. Answering "Yes" to a particular question states that the implementation supports all the mandatory procedures for that function defined in the referenced clauses and subclauses of ETS 300 402-2 [1]. Answering "No" to a particular question states that the implementation does not support that function of the protocol.

Table A.12: Major capabilities - network

Item	Major capability: does the IUT support...	Conditions for status	Status	Reference	Support
General					
MCn 1.1	configurations using more than one Terminal Endpoint Identifier (TEI)?		O.8	Annex A	[]Yes [√]No
MCn 1.2	point-to-point configurations using only one TEI value?		O.8	Annex A	[√]Yes []No
Procedures for unacknowledged information transfer					
MCn 2.1	the unacknowledged information transfer service in the broadcast data link (using TEI value 127)?	MCn 3 NOT MCn 3	M O	5.2	[]Yes [√]No
MCn 2.2	the unacknowledged information transfer service in a point-to-point data link (using a TEI value other than 127)?		O	5.2, 5.2.1	[]Yes [√]No
TEI management procedure					
MCn 3	TEI management procedures?	MCn 1.1 MCn 1.2	M O	5.3 Annex A	[]Yes [√]No
MCn 3.1.1	the automatic TEI assignment procedures?	MCn 3 NOT MCn 3	M N/A	5.3.2	[]Yes []No [√]N/A
MCn 3.1.2	the non-automatic TEI assignment procedures?	MCn 3 NOT MCn 3	M N/A	5.3.2	[]Yes []No [√]N/A
MCn 3.2	the TEI check procedures?	MCn 3 NOT MCn 3	M N/A	5.3.3	[]Yes []No [√]N/A
MCn 3.3	the TEI removal procedures?	MCn 3 NOT MCn 3	M N/A	5.3.4	[]Yes []No [√]N/A
MCn 3.4	the TEI identity verify procedures?	MCn 3 NOT MCn 3	O N/A	5.3.5	[]Yes []No [√]N/A
Initialization of data link layer parameters					
MCn 4	the procedures for initialization of the data link parameters to the default values?		M	5.4	[√]Yes []No
Multiple frame operations					
MCn 5	multiple frame operations?		M	5.5	[√]Yes []No
MCn 5.1.1	the self initiated establishment of multiple frame operation?		O	5.5.1, 5.5.5, 5.5.6	[√]Yes []No
MCn 5.1.2	the peer initiated establishment of multiple frame operation?		M	5.5.1, 5.5.5, 5.5.6	[√]Yes []No
MCn 5.2.1	the self initiated termination of multiple frame operation?		O	5.5.3, 5.5.5, 5.5.6	[√]Yes []No
MCn 5.2.2	the peer initiated termination of multiple frame operation?		M	5.5.3, 5.5.5, 5.5.6	[√]Yes []No
MCn 5.3	information transfer in multiple frame operation?		M	5.6	[√]Yes []No
MCn 5.4	the re-establishment of multiple frame operation?		M	5.7	[√]Yes []No
MCn 5.5	the data link layer monitor function?		O	5.10	[√]Yes []No
O.8	Support of one and only one of these options is required.				
Comments:					

A.8.2 Subsidiary capabilities

Indicating support for an item in table A.13 states that the implementation supports special cases or options within a major capability.

Table A.13: Subsidiary capabilities - network

Item	Subsidiary capability: does the IUT support...	Conditions for status	Status	Reference	Support
SCn 1	not used				
Multiple frame operations					
SCn 2	the transmission of I frames in the own receiver busy condition?		O	5.6.1	[]Yes [√]No
Comments:					
SCn 2: Some, but not all, BT network implementations support this feature.					

A.8.3 Protocol data units

The tables in this subclause ask questions related to the support of PDUs in the network role.

A.8.3.1 Frames received by the network

Indicating support for an item in table A.14 states that the implementation has the ability to recognize the frame listed in that item. Support for the receipt of a particular type of PDU means support for recognizing and acting upon all valid instances of that PDU type, including all valid PDU parameters, to the extent required by ETS 300 402-2 [1].

Table A.14: Frames received - network

Item	Message: does the IUT support the receipt of a frame of type...	Conditions for status	Status	Reference	Support
Information transfer (I) format					
FRn 1	I command?		M	3.6.2, 5.6	[√]Yes []No
Supervisory (S) format					
FRn 2	RR command?		M	3.6.6, 5.6, 5.10	[√]Yes []No
FRn 3	RR response?		M	3.6.6, 5.6, 5.10	[√]Yes []No
FRn 4	RNR command?		M	3.6.8, 5.6, 5.10	[√]Yes []No
FRn 5	RNR response?		M	3.6.8, 5.6, 5.10	[√]Yes []No
FRn 6	REJ command?		M	3.6.7, 5.6, 5.8.1	[√]Yes []No
FRn 7	REJ response?		M	3.6.7, 5.6, 5.8.1	[√]Yes []No
Unnumbered (U) format					
FRn 8	SABME command?		M	3.6.3, 5.5.1, 5.7	[√]Yes []No
FRn 9	DISC command?		M	3.6.4, 5.5.3	[√]Yes []No
FRn 10	UA response?		M	3.6.9, 5.5	[√]Yes []No
FRn 11	DM response?		M	3.6.10, 5.5	[√]Yes []No
FRn 12	UI command?	MCn 2.1 OR MCn 2.2 NOT (MCn 2.1 OR MCn 2.2)	M N/A	3.6.5, 5.2.3, 5.3	[]Yes []No [√]N/A
FRn 13	FRMR response?		M	3.6.11, 5.8.6	[√]Yes []No
FRn 14	XID command?		M	3.6.12	[√]Yes []No Note 1
FRn 15	XID response?		M	3.6.12	[√]Yes []No Note 1
Comments:					
Note 1: Command understood by the protocol, but explicitly not acted upon.					

A.8.3.2 Frames transmitted by the network

Indicating support for an item in table A.15 states that the implementation has the ability to transmit the frame listed in that item.

Table A.15: Frames transmitted - network

Item	Message: does the IUT support the transmission of a frame of type...	Conditions for status	Status	Reference	Support
Information transfer (I) format					
FTn 1	I command?		M	3.6.2, 5.6	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
Supervisory (S) format					
FTn 2	RR command?		M	3.6.6, 5.6, 5.10	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 3	RR response?		M	3.6.6, 5.6, 5.10	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 4	RNR command?		M	3.6.8, 5.6, 5.10	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 5	RNR response?		M	3.6.8, 5.6, 5.10	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 6	REJ command?		M	3.6.7, 5.6, 5.8.1	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 7	REJ response?		M	3.6.7, 5.6, 5.8.1	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
Unnumbered (U) format					
FTn 8	SABME command?		M	3.6.3, 5.5.1, 5.7	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 9	DISC command?	MCn 5.2.1 NOT MCn 5.2.1	M O	3.6.4, 5.5.3	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 10	UA response?		M	3.6.9, 5.5	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 11	DM response?		M	3.6.10, 5.5	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
FTn 12	UI command?	MCn 2.1 OR MCn 2.2 NOT (MCn 2.1 OR MCn 2.2)	M N/A	3.6.5, 5.2.2, 5.3	<input type="checkbox"/> Yes <input type="checkbox"/> No <input checked="" type="checkbox"/> N/A
FTn 13	FRMR response?		X	3.6.11, 5, 5.8.6	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No
Comments:					

A.8.4 PDU parameters

A.8.4.1 Service data units

A.8.4.1.1 Service data units received by the network

The tables in this subclause ask questions related to the support of SDU parameters in UI frames received and transmitted by the IUT in the network role.

Table A.16: SDUs received in UI frames - network

Item	Does the IUT support in the UI frame information field the interpretation of ...	Conditions for status	Status	Reference	Support
PRn 1	Layer 3 messages?	FRn 12 NOT FRn 12	O N/A	5.2	<input type="checkbox"/> Yes <input type="checkbox"/> No <input checked="" type="checkbox"/> N/A
Layer management messages					
PRn 2.1	Identity request?	MCn 3.1.1 NOT MCn 3.1.1	M N/A	5.3.2	<input type="checkbox"/> Yes <input type="checkbox"/> No <input checked="" type="checkbox"/> N/A
PRn 2.2	Identity check response?	MCn 3.2 NOT MCn 3.2	M N/A	5.3.3	<input type="checkbox"/> Yes <input type="checkbox"/> No <input checked="" type="checkbox"/> N/A
PRn 2.3	Identity verify?	MCn 3.4 NOT MCn 3.4	M N/A	5.3.5	<input type="checkbox"/> Yes <input type="checkbox"/> No <input checked="" type="checkbox"/> N/A
Comments:					

A.8.4.1.2 Service data units transmitted by the network

Table A.17: SDUs transmitted in UI frames - network

Item	Does the IUT support in the UI frame information field the inclusion of ...	Conditions for status	Status	Reference	Support
PTn 1	Layer 3 messages?	FTn 12 NOT FTn 12	O N/A	5.2	[]Yes []No [√]N/A
Layer management messages					
PTn 2.1	Identity assign?	MCn 3.1.1 NOT MCn 3.1.1	M N/A	5.3.2	[]Yes []No [√]N/A
PTn 2.2	Identity denied?	MCn 3.1.1 NOT MCn 3.1.1	M N/A	5.3.2	[]Yes []No [√]N/A
PTn 2.3	Identity check request?	MCn 3.2 NOT MCn 3.2	M N/A	5.3.3	[]Yes []No [√]N/A
PTn 2.4	Identity remove?	MCn 3.3 NOT MCn 3.3	M N/A	5.3.4	[]Yes []No [√]N/A
Comments:					

A.8.4.2 Address field variables

The tables in this subclause ask questions related to the support of the values of certain fields of the address field received and transmitted by the IUT in the network role.

Table A.18: SAPI values supported - network

Item	Does the IUT support the ...	Conditions for status	Status	Reference	Support
SAPn 1	SAPI value 0?		O.9	3.3.3	[√]Yes []No
SAPn 2	SAPI value 12?		O.9	3.3.3	[]Yes [√]No
SAPn 3	SAPI value 16?		O.9	3.3.3	[]Yes [√]No
SAPn 4	SAPI value 63?	MCn 3 NOT MCn 3	M N/A	3.3.3, 5.3.1	[]Yes []No [√]N/A
O.9 Support of at least one of these options is required.					
Comments:					

Table A.19: TEI values supported - network

Item	Does the IUT support the...	Conditions for status	Status	Reference	Support
TEIn 1	TEI value 0 exclusively?	MCn 1.2 NOT MCn 1.2	M N/A	3.3.4.2, Annex A	[√]Yes []No []N/A
TEIn 2	TEI values in the range from 0 to 63?	MCn 3.1.2 NOT MCn 3.1.2	M N/A	3.3.4.2	[]Yes []No [√]N/A
TEIn 3	TEI values in the range from 64 to 126?	MCn 3.1.1 NOT MCn 3.1.1	M N/A	3.3.4.2	[]Yes []No [√]N/A
TEIn 4	TEI value 127?	MCn 2.1 NOT MCn 2.1	M N/A	3.3.4.1	[]Yes []No [√]N/A
Comments:					

A.8.5 Timers

Indicating support for an item in table A.20 states that the implementation has a timer that operates in accordance with the description in subclause 5.9 and the relevant behaviour in ETS 300 402-2 [1].

Table A.20: Timers - network

Item	Timer: does the IUT support...	Conditions for status	Status	Reference	Support	Supported value(s)
TMn 1	T200 (default value 1 s)?		M	5.9.1	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No	1 s
TMn 2	T201 (default value 1 s)?	MCn 1.1 MCn 1.2	M N/A	5.9.6	<input type="checkbox"/> Yes <input type="checkbox"/> No <input checked="" type="checkbox"/> N/A	
TMn 3	T203 (default value 10 s)?	MCn 5.5 NOT MCn 5.5	M N/A	5.9.8	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No <input type="checkbox"/> N/A	10 s
Comments:						

A.8.6 System parameters

Indicating support for an item in table A.21 states that the implementation has implemented the system parameter.

Table A.21: Parameters - network

Item	System parameter: does the IUT support...	Conditions for status	Status	Reference	Support	Supported value(s)
SPn 1	N200 (default value 3)?		M	5.9.2	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No	3
SPn 2	N201 (default value 260)?		M	5.9.3	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No	260
SPn 3	k (default values 1, 3, 7)?		M	5.9.5	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No	7
Comments:						

4. History

Issue 1	November 2000	First Issue
Issue 1.1	November 2006	Addition of note against SCn 2 in Table 13 and correction of entry against SAPn 4 in Table 18.
Issue 1.2	July 2014	Change SINet site references from http://www.sinet.bt.com to http://www.btplc.com/sinet/
Issue 1.3	October 2020	Changes to branding, from BT to Openreach including changes to reflect new Openreach SIN site and Openreach SIN email address
Issue 1.3	October 2021	Annual Review – no changes required – issue remains unchanged.

End